

870 Order Status Report - Canada

VICS EDI

Version: 005040VICS

Author: GS1 US & GS1 Canada

Publication: 12/31/2007

Notes: July, 2008 Implementation

Table of Contents

870	Order Status Report - Canada	'
ST	Transaction Set Header	5
BSF	R Beginning Segment for Order Status Report	€
N1	Loop Party Identification	7
N1	Party Identification	
HL	Loop Hierarchical Level	9
HL	Hierarchical Level	
PRF	Purchase Order Reference	11
HL	Loop Item	12
HL	Hierarchical Level	13
PO1	Loop Baseline Item Data	14
PO1	Baseline Item Data	15
ISR		
ISR		
QTY	•	
REF	Reference Information	20
CTT	Transaction Totals	21
SE	Transaction Set Trailer	

870

Order Status Report - Canada

Functional Group=RS

Purpose: This X12 Transaction Set contains the format and establishes the data contents of the Order Status Report Transaction Set (870) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to report on the current status of a requirement forecast, an entire purchase order, selected line items on a purchase order, selected products/services on a purchase order, or purchase orders for a specific customer in their entirety or on a selection basis. The transaction set can also be used to report on the current status of single or multiple requisitions. The report format allows for the inclusion of "reasons" relative to the status. This transaction set may also be used to update the supplier's scheduled shipment or delivery dates. This transaction set can result from either an inquiry or a prearranged schedule agreed to by the trading partners.

This is a functional profile of the 870 transaction for use in Canada.

Heading:

пеаищ	y .							
<u>Pos</u>	<u>ld</u>	Segment Name	Req	Max Use	Repeat	<u>Notes</u>	<u>Usage</u>	<u>Page</u>
0100	ST	Transaction Set Header	M	1			Must use	5
0200	BSR	Beginning Segment for Order Status Report	М	1			Must use	6
* 0420	TD3	Carrier Details (Equipment)	0	1				N/A
* 0430	TD4	Carrier Details (Special Handling, or Hazardous Materials, or Both)	0	1				N/A
* 0440	TD5	Carrier Details (Routing Sequence/Transit Time)	0	1				N/A
* 0450	DTM	Date/Time Reference	0	10				N/A
* LOOF	D - RE	<u>F</u>			<u>>1</u>			N/A
0460	REF	Reference Information	0	1				N/A
* 0470	DTM	Date/Time Reference	0	>1				N/A
LOOP	ID - N1				200			7
0500	N1	Party Identification	0	1			Used	8
* 0600	N2	Additional Name Information	0	2				N/A
* 0700	N3	Party Location	0	2				N/A
* 0800	N4	Geographic Location	0	1				N/A
* 0900	REF	Reference Information	0	12				N/A
* 1000	PER	Administrative Communications Contact	0	3				N/A
* 1050	PWK	Paperwork	0	1				N/A
* 1 005	D - LM	l			<u>10</u>			N/A
* 1200	LM	Code Source Information	0	1	10			N/A N/A
* 1300	LQ	Industry Code	M	100				N/A
1300	LQ	Identification	171	100				IN/A

Detail:

<u>Pos</u>	<u>ld</u>	Segment Name	Req	Max Use	Repeat	<u>Notes</u>	<u>Usage</u>	<u>Page</u>
LOOP	ID - HL				<u>1000</u>			9
0100	HL	Hierarchical Level	M	1			Must use	10
0200	PRF	Purchase Order Reference	0	1			Must use	11
* LOOF	D - ISI	<u>R</u>	•		<u>104</u>	· ·		N/A
0300	ISR	Item Status Report	0	1				N/A

* 0400	PID	Draduat/Itam Description	0	e		11
* 0500	QTY	Product/Item Description Quantity Information	0	6 4		
* 0700	PER	Administrative	0	3		<u>_</u>
0700	I LIX	Communications Contact	O	0		
* 0800	DTM	Date/Time Reference	0	10		
* 0860	CS	Contract Summary	0	3		N2/0860
	D - RE				>1	
0870	REF	Reference Information	0	1		
* 0880	DTM	Date/Time Reference	O	>1		
					222	
	P ID - N1 N1	Party Identification	_	4	<u>200</u>	
0900			0	1		
1000	N2	Additional Name Information	0	2		
1100	N3	Party Location	0	2		
1200	N4	Geographic Location	0	1		
1300	REF	Reference Information	0	12		
1400	PER	Administrative	0	3		
1400	FEK	Communications Contact	J	3		
	P ID - LN		_	,	<u>10</u>	
1440	LM	Code Source Information	0	1		
1450	LQ	Industry Code	M	100		
		Identification				
	P ID - PC	<u>)1</u>			<u>1000</u>	
1500	PO1	Baseline Item Data	0	1		
1550	CUR	Currency	0	1		
1600	SLN	Subline Item Detail	0	100		
1700	PO3	Additional Item Detail	0	1		
1800	PID	Product/Item Description	0	1000		
1900	MEA	Measurements	0	40		
2000	PKG	Marking, Packaging,	0	25		
*		Loading				·
	P ID - ISF		^	4	<u>104</u>	
2100	ISR	Item Status Report	0	1		
2200	PID	Product/Item Description	0	6		
2300	QTY	Quantity Information	0	4		
2400	DTM	Date/Time Reference	0	10		
2500	N1	Party Identification	0	1		
2510	N2	Additional Name	0	2		
2520	NO	Information	^	2		
2520	N3	Party Location	0	2		
2530	N4	Geographic Location	0	1		
2600	TD1	Carrier Details (Quantity and Weight)	0	1		
2700	TD5	Carrier Details (Routing	0	1		
2700	פטו	Sequence/Transit Time)	J	ı		
2800	TD3	Carrier Details	0	1		
2000	נטו	(Equipment)	J	ı		
		Carrier Details (Special	0	1		
2900	TD4		_	'		
2900	TD4					111
2900	TD4	Handling, or Hazardous Materials, or Both)				
	TD4	Handling, or Hazardous	0	12		
* 2900 * 3000 * 3100		Handling, or Hazardous Materials, or Both) Reference Information	0	12 25		
3000	REF	Handling, or Hazardous Materials, or Both)				

* 1 005					40		<u> </u>]
	PID - LN		_	4	<u>10</u>			N/A
* 3200	LM	Code Source Information	0	1				N/A
* 3300	LQ	Industry Code Identification	М	100				N/A
* 1 005	P ID - LX				<u>>1</u>	N2/3400L		- - - - N/A
* 3400	LX	Transaction Set Line	0	1	<u> </u>	N2/3400L		N/A
3-100	LX	Number	O	'		142/5400		
* 3500	REF	Reference Information	0	>1				N/A
* 3600	N1	Party Identification	0	1				N/A
* 3700	DTM	Date/Time Reference	0	10				N/A
* LOOF	D - LN	1			<u>10</u>			N/A
* 3800	LM	Code Source Information	0	1				N/A
* 3900	LQ	Industry Code	M	100				N/A
		Identification						
LOOP	ID - HL				1000			12
0100	HL	Hierarchical Level	М	1			Must use	13
* 0200	PRF	Purchase Order	0	1				N/A
		Reference						
	PID - ISI				<u>104</u>			N/A
* 0300	ISR	Item Status Report	0	1				N/A
* 0400	PID	Product/Item Description	0	6				N/A
* 0500	QTY	Quantity Information	0	4				N/A
* 0700	PER	Administrative Communications Contact	0	3				N/A
* 0800	DTM	Date/Time Reference	0	10				N/A
* 0860	CS	Contract Summary	0	3		N2/0860		N/A
	P ID - RE				<u>>1</u>	142/0000		N/A
* 0870	REF	Reference Information	0	1	<u></u>			N/A
* 0880	DTM	Date/Time Reference	Ō	>1				N/A
* 1 00	P ID - N1				200			 N/A
* 0900	N1	Party Identification	0	1	<u>200</u>			N/A
* 1000	N2	Additional Name	0	2				N/A
1000	112	Information	Ū	_				
* 1100	N3	Party Location	0	2				N/A
* 1200	N4	Geographic Location	0	1				N/A
* 1300	REF	Reference Information	0	12				N/A
* 1400	PER	Administrative	0	3				N/A
		Communications Contact						
* LOOF	P ID - LN	1			<u>10</u>			N/A
* 1440	LM	Code Source Information	0	1				N/A
* 1450	LQ	Industry Code	M	100				N/A
		Identification						
LOOP	ID - PO1				1000			14
1500	PO1	Baseline Item Data	0	1	1000		Used	15
* 1550	CUR	Currency	Ö	1				N/A
* 1600	SLN	Subline Item Detail	Ö	100				N/A
* 1700	PO3	Additional Item Detail	0	1				N/A
* 1800	PID	Product/Item Description	0	1000				N/A
* 1900	MEA	Measurements	0	40				N/A
* 2000	PKG	Marking, Packaging,	0	25				N/A
		Loading						-
LOOP	<u>ID - ISR</u>				<u>104</u>			17

2100	ISR	Item Status Report	0	1			Must use	18
* 2200	PID	Product/Item Description	0	6				N/A
2300	QTY	Quantity Information	0	4			Used	19
* 2400	DTM	Date/Time Reference	0	10				N/A
* 2500	N1	Party Identification	0	1				N/A
* 2510	N2	Additional Name Information	0	2				N/A
* 2520	N3	Party Location	0	2				N/A
* 2530	N4	Geographic Location	0	1				N/A
* 2600	TD1	Carrier Details (Quantity and Weight)	0	1				N/A
* 2700	TD5	Carrier Details (Routing Sequence/Transit Time)	0	1				N/A
* 2800	TD3	Carrier Details (Equipment)	0	1				N/A
* 2900	TD4	Carrier Details (Special Handling, or Hazardous Materials, or Both)	0	1				N/A
3000	REF	Reference Information	0	12			Used	20
* 3100	SAC	Service, Promotion, Allowance, or Charge Information	0	25				N/A
* LOOF	D - LM		•		<u>10</u>	•		N/A
* 3200	LM	Code Source Information	0	1				N/A
* 3300	LQ	Industry Code Identification	М	100				N/A
* I 00F	D - LX				>1	N2/3400L		∃∐ _{N/A}
* 3400	LX	Transaction Set Line Number	0	1		N2/3400		N/A
* 3500	REF	Reference Information	0	>1				III N/A
* 3600	N1	Party Identification	0	1				N/A
* 3700	DTM	Date/Time Reference	0	10				N/A
	D - LM	· · · · · · · · · · · · · · · · · · ·			<u>10</u>			N/A
* 3800	LM	Code Source Information	0	1	_			N/A
* 3900	LQ	Industry Code Identification	M	100				N/A

Summary:

<u>Pos</u>	<u>ld</u>	Segment Name	Req	Max Use	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>	<u>Page</u>
0100	CTT	Transaction Totals	0	1		N3/0100	Used	21
0200	SE	Transaction Set Trailer	M	1			Must use	22

Notes:

2/0860 Use is limited to intra-organizational transactions.

2/3400L The LX loop conveys serial number, lot number, and inventory data.

2/3400 The LX loop conveys serial number, lot number, and inventory data.

2/0860 Use is limited to intra-organizational transactions.

2/3400L The LX loop conveys serial number, lot number, and inventory data.

2/3400 The LX loop conveys serial number, lot number, and inventory data.

3/0100 The number of line items (CTT01) is the accumulation of the number of HL segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

GS1 US & GS1 Canada

Transaction Set Header

Pos: 0100 Max: 1 **Heading - Mandatory** Loop: N/A Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>ld</u>	Element Na	<u>ime</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction	n Set Identifier Code	М	ID	3/3	Must use
		Description	n: Code uniquely identifying a T	ransactio	n Set		
		CodeList S	ummary (Total Codes: 319, Inc	cluded: 1))		
		<u>Code</u>	<u>Name</u>				
		870	Order Status Report				
ST02	329	Transaction	n Set Control Number	М	AN	4/9	Must use
		Description	: Identifying control number tha	at must b	e unique	within the tran	saction set

functional group assigned by the originator for a transaction set

The number is sequentially assigned by the sender, starting with one within each functional group. For each functional group, the first transaction set control number will be 0001 and incremented by one for each additional transaction set within the group.

Semantics:

- 1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
- 2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

BSR Beginning Segment for Order Status Report

Pos: 0200 Max: 1 Heading - Mandatory Loop: N/A Elements: 4

User Option (Usage): Must use

Purpose: To indicate the beginning of an Order Status Report Transaction Set

Element Summary:

Ref BSR01	<u>ld</u> 850	Element Na Status Repo		<u>Req</u> M	<u>Type</u> ID	Min/Max 1/2	<u>Usage</u> Must use
		Description	: Code indicating the reason for	sendin	g the rep	ort	
		CodeList So Code 1 2 3	ummary (Total Codes: 12, Inclu Name Response to an Order Status Prearranged Schedule or Agre Unsolicited Report	Inquiry	(869)		
BSR02	847	Order/Item	Code	М	ID	1/2	Must use
		Description	: Code identifying a group of or	ders and	d items		
		CodeList So Code PP	ummary (Total Codes: 8, Includ Name Selected Orders - Selected Ite The item levels represent the	ems	of only tl	hose specific it	ems requested.
BSR03	127	Reference I	dentification	М	AN	1/80	Must use
		specified by	: Reference information as define the Reference Identification Quality in the sender to identify the sender t	alifier			
BSR04	373	Date		M	DT	8/8	Must use
		Description the calendar	: Date expressed as CCYYMMI year	DD whe	re CC rep	presents the fire	st two digits of

Semantics:

- 1. BSR03 indicates a status report document number assigned by the sender.
- 2. BSR04 indicates the date of this report from the sender.
- 3. BSR07 indicates the time of this report from the sender.
- 4. BSR08 indicates a status report document number assigned by the inquirer.
- 5. BSR09 indicates the date this report was requested from the sender by the inquirer.
- 6. BSR10 indicates the time this report was requested from the sender by the inquirer.

Loop Party Identification

Pos: 0500 Repeat: 200 Optional

Loop: N1 Elements: N/A

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

<u>Pos</u>	<u>ld</u>	Segment Name	<u>Req</u>	Max Use	Repeat	<u>Usage</u>
0500	N1	Party Identification	0	1		Used

N1 Party Identification

Pos: 0500 Max: 1 Heading - Optional Loop: N1 Elements: 4

<u>Usage</u>

Min/Max

User Option (Usage): Used

Purpose: To identify a party by type of organization, name, and code

Element Name

Element Summary:

ld

Ref

N101	98	Entity Ide	entifier Code	М	ID	2/3	Must use	
		Descripti individual	on: Code identifying an organiz	ational ent	tity, a phy	sical location	, property or an	
		CodeList Code SF	Summary (Total Codes: 1504, <u>Name</u> Ship From	Included:	1)			
N102	93	Name		X	AN	1/60	Used	
		Descripti	on: Free-form name					
N103	66	Identifica	tion Code Qualifier	X	ID	1/2	Must use	
		Descripti Code (67)	on: Code designating the system	of code s	tructure used	for Identification		
			Summary (Total Codes: 249, I	ncluded: 6	5)			
		<u>Code</u>	Name					
		1	D-U-N-S Number, Dun & Bi See External Code Source		otion III fo	r reference d	looumont	
		9	D-U-N-S+4, D-U-N-S Numb				ocument.	
		9	See External Code Source				locument	
		21	Health Industry Number (HI		Cuon in ic	r reference d	ocument.	
		21	See External Code Source		ection III i	or reference	document.	
		91	Assigned by Seller or Seller	-		0 0. 0. 0 0	a common a	
		92	Assigned by Buyer or Buye	_				
		UL						
			Description: A globally un	ique 13 di	git code fo	or the identific	cation of a legal,	

67 Identification Code

AN 2/80

functional or physical location within the Uniform Code Council (UCC) and International Article Number Association (EAN) numbering system

See External Code Source 583 in Section III for reference document.

Must use

Description: Code identifying a party or other code

This is the location code as defined by N103. The location code may be a formal number, e.g., DUNS, or it may be assigned by either the buyer or seller. The location refers to a store, warehouse, distribution center, plant, etc. Location codes are used to alleviate the need to send complete names and addresses.

This is the 13-digit Global Location Number (GLN).

Syntax Rules:

N104

- 1. R0203 At least one of N102 or N103 is required.
- 2. P0304 If either N103 or N104 is present, then the other is required.

Comments:

- This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
- 2. N105 and N106 further define the type of entity in N101.

Loop Hierarchical Level

Pos: 0100 Repeat: 1000 Mandatory Loop: HL Elements: N/A

User Option (Usage): Must use

Purpose: To identify dependencies among and the content of hierarchically related groups of data segments

<u>Pos</u>	<u>ld</u>	Segment Name	<u>Req</u>	Max Use	Repeat	<u>Usage</u>
0100	HL	Hierarchical Level	M	1		Must use
0200	PRF	Purchase Order Reference	0	1		Must use

HI Hierarchical Level

Pos: 0100 Max: 1 Detail - Mandatory Loop: HL Elements: 2

User Option (Usage): Must use

Purpose: To identify dependencies among and the content of hierarchically related groups of data segments

The HL segment is used to identify levels of detail information using a hierarchical structure.

HL01 shall contain a unique number for each occurrence of the HL segment within the transaction set. The value assigned to the first HL segment will be 1, and is incremented by one for each subsequent HL segment within the transaction set.

HL02 identifies the hierarchical ID of the HL segment to which it is subordinate (child of). HL02 will be omitted for the order level HL segment (HL03 contains code O), since it has no parent. HL03 identifies the application context of the series of segments following the current HL segment up to the next occurrence of an HL segment, or the CTT or SE segment, e.g., Order and Item.

Element Summary:

Ref	<u>ld</u>	Element Name	Req	Type	Min/Max	<u>Usage</u>
HL01	628	Hierarchical ID Number	M	AN	1/12	Must use
		Description: A unique number assigned by in a hierarchical structure	the sen	der to ide	entify a particu	lar data segment
HL03	735	Hierarchical Level Code	М	ID	1/2	Must use
		Description: Code defining the characterist	tic of a le	evel in a l	nierarchical str	ructure
		CodeList Summary (Total Codes: 250, Inc	luded: 1)		
		Code Name				
		O Order				

Comments:

- 1. The HL segment is used to identify levels of detail information using a hierarchical structure, such as relating line-item data to shipment data, and packaging data to line-item data.
- 2. The HL segment defines a top-down/left-right ordered structure.
- 3. HL01 shall contain a unique alphanumeric number for each occurrence of the HL segment in the transaction set. For example, HL01 could be used to indicate the number of occurrences of the HL segment, in which case the value of HL01 would be "1" for the initial HL segment and would be incremented by one in each subsequent HL segment within the transaction.
- 4. HL02 identifies the hierarchical ID number of the HL segment to which the current HL segment is subordinate.
- 5. HL03 indicates the context of the series of segments following the current HL segment up to the next occurrence of an HL segment in the transaction. For example, HL03 is used to indicate that subsequent segments in the HL loop form a logical grouping of data referring to shipment, order, or item-level information.
- 6. HL04 indicates whether or not there are subordinate (or child) HL segments related to the current HL segment.

PRF Purchase Order Reference

Pos: 0200 Max: 1 Detail - Optional Loop: HL Elements: 2

User Option (Usage): Must use

Purpose: To provide reference to a specific purchase order

Element Summary:

Ref	<u>ld</u>	Element Name	Req	Type	Min/Max	<u>Usage</u>
PRF01	324	Purchase Order Number	М	AN	1/22	Must use
		Description: Identifying number for Purchase Retailer's original purchase order number	se Orde	r assigne	ed by the order	er/purchaser
PRF04	373	Date	0	DT	8/8	Used
		Description: Date expressed as CCYYMMI the calendar year	DD whe	re CC rep	oresents the fir	st two digits of
		Retailer's original purchase order date				

Semantics:

1. PRF04 is the date assigned by the purchaser to purchase order.

Loop Item

Pos: 0100 Repeat: 1000 Mandatory Loop: HL Elements: N/A

User Option (Usage): Must use

Purpose: To identify dependencies among and the content of hierarchically related groups of data segments

Pos	<u>ld</u>	Segment Name	Req	Max Use	Repeat	<u>Usage</u>
0100	HL	Hierarchical Level	M	1		Must use
1500		Loop PO1	0		1000	Used

Retail Industry Conventions & Implementation Guidelines for EDI

HI Hierarchical Level

Pos: 0100 Max: 1 Detail - Mandatory Loop: HL Elements: 2

User Option (Usage): Must use

Purpose: To identify dependencies among and the content of hierarchically related groups of data segments

The HL segment is used to identify levels of detail information using a hierarchical structure.

HL01 shall contain a unique number for each occurrence of the HL segment within the transaction set. The value assigned to the first HL segment will be 1, and is incremented by one for each subsequent HL segment within the transaction set.

HL02 identifies the hierarchical ID of the HL segment to which it is subordinate (child of). HL02 will be omitted for the order level HL segment (HL03 contains code O), since it has no parent. HL03 identifies the application context of the series of segments following the current HL segment up to the next occurrence of an HL segment, or the CTT or SE segment, e.g., Order and Item.

Element Summary:

Ref HL01	<u>ld</u> 628	Element Name Hierarchical ID Number	Req M	<u>Type</u> AN	Min/Max 1/12	<u>Usage</u> Must use
		Description: A unique number assigned by in a hierarchical structure	the sen	ider to ide	entify a particul	ar data segment
HL03	735	Hierarchical Level Code	М	ID	1/2	Must use
		Description: Code defining the characterist	ic of a le	evel in a	hierarchical str	ucture
		CodeList Summary (Total Codes: 250, Inc Code Name I Item	luded: 1)		

Loop Baseline Item Data

Pos: 1500 Repeat: 1000 Optional

Loop: PO1 Elements: N/A

User Option (Usage): Used

Purpose: To specify basic and most frequently used line item data

<u>Pos</u>	<u>ld</u>	Segment Name	Req	Max Use	Repeat	<u>Usage</u>
1500	PO1	Baseline Item Data	0	1		Used
2100		Loop ISR	0		104	Must use

PO1 Baseline Item Data

Pos: 1500 Max: 1 Detail - Optional Loop: PO1 Elements: 2

User Option (Usage): Used

Purpose: To specify basic and most frequently used line item data

There can be only one iteration of the PO1 loop at the item level to maintain a one-to-one relation between the PO1 segment and the item level HL segment.

Element Summary:

Ref	<u>ld</u>	Element Name	<u>Req</u>	Type	Min/Max	<u>Usage</u>
PO106	235	Product/Service ID Qualifier	Χ	ID	2/2	Must use

Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)

CodeList Summary (Total Codes: 530, Included: 5)

CodeNameCACase

GTIN EAN/UCC-14 digit Shipping Unit – the data structure for a 14-digit EAN.UCC Global Trade Item Number that uniquely identifies a manufacturer's shipping unit encompassing non-consumer trade units such as cases, pallets and inner packs. The number includes the packaging

indicator and check digit.

EN GTIN EAN/UCC - 13 Digit Data Structure

Description: Data structure for the 13 digit EAN.UCC (EAN

International.Uniform Code Council) Global Trade Item Number (GTIN)

EO GTIN EAN/UCC - 8 Digit Data Structure

Description: Data structure for the 8 digit EAN.UCC (EAN

International. Uniform Code Council) Global Trade Item Number (GTIN)

UK GTIN 14-digit Data Structure

Description: Data structure for the 14 digit EAN.UCC (EAN

International. Uniform Code Council) Global Trade Item Number (GTIN)

UP GTIN UCC - 12 Digit Data Structure

Description: Data structure for the 12 digit EAN.UCC (EAN

International. Uniform Code Council) Global Trade Item Number (GTIN).

Also known as the Universal Product Code (U.P.C.)

PO107 234 Product/Service ID X AN 1/48 Must use

Description: Identifying number for a product or service

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.

2. C0504 - If PO105 is present, then PO104 is required.

3. P0607 - If either PO106 or PO107 is present, then the other is required.

4. P0809 - If either PO108 or PO109 is present, then the other is required.

5. P1011 - If either PO110 or PO111 is present, then the other is required.

6. P1213 - If either PO112 or PO113 is present, then the other is required.

7. P1415 - If either PO114 or PO115 is present, then the other is required.

8. P1617 - If either PO116 or PO117 is present, then the other is required.

9. P1819 - If either PO118 or PO119 is present, then the other is required.

10. P2021 - If either PO120 or PO121 is present, then the other is required.

11. P2223 - If either PO122 or PO123 is present, then the other is required.

12. P2425 - If either PO124 or PO125 is present, then the other is required.

Semantics:

1. PO102 is quantity ordered.

Loop Item Status Report

Pos: 2100 Repeat: 104 Optional

Loop: ISR Elements: N/A

User Option (Usage): Must use

Purpose: To specify detailed purchase order/item status

<u>Pos</u>	<u>ld</u>	Segment Name	<u>Req</u>	Max Use	Repeat	<u>Usage</u>
2100	ISR	Item Status Report	0	1		Must use
2300	QTY	Quantity Information	0	4		Used
3000	REF	Reference Information	0	12		Used

ISR Item Status Report

Pos: 2100 Max: 1 Detail - Optional Loop: ISR Elements: 3

User Option (Usage): Must use

Purpose: To specify detailed purchase order/item status

Element Summary:

Ref ISR01	<u>ld</u> 368	Element Na Shipment/0	<u>ame</u> Order Status Code	<u>Req</u> M	Type ID	Min/Max 2/2	<u>Usage</u> Must use
		•	n: Code indicating the status of a petween the quantity ordered and		•		,
		CodeList S Code AS DS ED EW IC	Summary (Total Codes: 102, Incl Name Available Now - Scheduled to Out Of Stock Condition Expect to Ship By (Date) Expect To Ship Week of (Date Item Canceled	Ship (da			
ISR02	373	Date Description the calenda	n: Date expressed as CCYYMMI	O DD whe	DT re CC rep	8/8 presents the fire	Used st two digits of
		If ISR01 co.	ntains code AS, BP, CC, CP, ED				
ISR03	641	Status Rea	ison Code	0	ID	3/3	Used

Description: Code indicating the status reason

CodeList Summary (Total Codes: 438, Included: 3)

Code Name

P03 Production Falldown

Description: Shipper held order for stock

W01 Out of Stock W08 Material Shortage

Semantics:

1. If ISR01 specifies a date, ISR02 is required.

QTY Quantity Information

Pos: 2300 Max: 4 Detail - Optional Loop: ISR Elements: 3

User Option (Usage): Used

Purpose: To specify quantity information

This represents the quantity associated with the previous ISR segment.

Element Summary:

Ref QTY01	<u>ld</u> 673	Element Name Quantity Qualifier	<u>Req</u> M	<u>Type</u> ID	Min/Max 2/2	<u>Usage</u> Must use
		Description: Code specifying the type of qu	antity			
		CodeList Summary (Total Codes: 1132, In Code Name 01 Discrete Quantity	cluded:	1)		
QTY02	380	Quantity	Χ	R	1/15	Must use
		Description: Numeric value of quantity				
QTY03	C001	Composite Unit of Measure	0	Comp		Used
		Description: To identify a composite unit of of use) Comments: 1. If C001-02 is not used, its value is to be in 2. If C001-03 is not used, its value is to be in 3. If C001-05 is not used, its value is to be in 4. If C001-06 is not used, its value is to be in 5. If C001-08 is not used, its value is to be in 6. If C001-09 is not used, its value is to be in 7. If C001-11 is not used, its value is to be in 9. If C001-14 is not used, its value is to be in 10. If C001-15 is not used, its value is to be	nterpreto nterpreto nterpreto nterpreto nterpreto nterpreto nterpreto	ed as 1.		dix for examples
QTY03-01	355	Unit or Basis for Measurement Code	M	ID	2/2	Must use

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

CodeList Summary (Total Codes: 884, Included: 5)

CodeNameBOBottleBXBoxCACaseEAEach

PL Pallet/Unit Load

Syntax Rules:

- 1. E0204 Only one of QTY02 or QTY04 may be present.
- 2. R0204 At least one of QTY02 or QTY04 is required.

Semantics:

1. QTY04 is used when the quantity is non-numeric.

REF Reference Information

Pos: 3000 Max: 12 Detail - Optional Loop: ISR Elements: 2

User Option (Usage): Used

Purpose: To specify identifying information

Element Summary:

RefIdElement NameReqTypeMin/MaxUsageREF01128Reference Identification QualifierMID2/3Must use

Description: Code qualifying the Reference Identification

CodeList Summary (Total Codes: 1767, Included: 1)

Code Name

CO Customer Order Number

Customer of retailer

REF02 127 Reference Identification X AN 1/80 Must use

Description: Reference information as defined for a particular Transaction Set or as

specified by the Reference Identification Qualifier

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

CTT Transaction Totals

Pos: 0100 Max: 1 Summary - Optional Loop: N/A Elements: 1

User Option (Usage): Used

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>ld</u>	Element Name	<u>Req</u>	<u>Type</u>	Min/Max	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use

Description: Total number of line items in the transaction set *The number of HL segments present in the transaction set*

Syntax Rules:

- 1. P0304 If either CTT03 or CTT04 is present, then the other is required.
- 2. P0506 If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

SE Transaction Set Trailer

Pos: 0200 Max: 1 Summary - Mandatory Loop: N/A Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

Ref	<u>ld</u>	Element Name	Req	Type	Min/Max	<u>Usage</u>	
SE01	96	Number of Included Segments	М	N0	1/10	Must use	
		Description: Total number of segments inc segments	luded in	a transa	ction set includ	ling ST and SE	
SE02	329	Transaction Set Control Number	М	AN	4/9	Must use	
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set					
		This must be the same number as is in the	ST segr	nent (ST	02) for the trans	saction set.	

Comments:

1. SE is the last segment of each transaction set.